

Technical alarm detectors for domestic premises

smoke alarm detectors, monoxide alarm detector, accessories



0 405 17



0 405 28



0 405 10

| Pack | Cat.Nos | Stand alone smoke alarm detector |
|------|----------|---|
| 1 | 0 405 17 | <p>Detects the smoke</p> <p>Conform to EN 14604, CE CPR and NF DAAF approved (by AFNOR certification)</p> <p>Photoelectric technology guarantee without radioelement</p> <p>Gives a loud signal: 85 dB at 3 meters</p> <p>Powered by lithium battery (lifetime: 10 years, not replaceable)</p> <p>Life cycle of 10 years: Due date indicated on the product</p> <p>Fitted with:</p> <ul style="list-style-type: none"> - "hush function": in case of false alarm permit to stop the alarm sound for 10 minutes - grid insect protection (to avoid false alarm) - "anti-theft function" (suitable for rental housing - a tool is necessary to take off the detector) <p>Delivered with screws and battery</p> |
| 1 | 0 405 28 | <p>Wireless interconnectable smoke alarm detector</p> <p>Detects the smoke</p> <p>Conform to EN 14604 and CE CPR and NF DAAF approved (by AFNOR certification)</p> <p>Photoelectric technology guarantee without radioelement</p> <p>Gives a loud signal - 85 dB at 3 meters</p> <p>Powered by lithium battery (lifetime: 10 years, not replaceable)</p> <p>Life cycle of 10 years: Due date indicated on the product</p> <p>Can be interconnected with 10 devices</p> <ul style="list-style-type: none"> - Cat.No 0 405 28 (smoke alarm detector) or - Cat.No 0 405 14 (relay) <p>When one device detects, all interconnected devices go into alarm</p> <p>Can be interconnected with My Home intruder alarm</p> <p>Suitable for housing with more one floor or more one device</p> <p>Fitted with:</p> <ul style="list-style-type: none"> - "hush function": in case of false alarm permit to stop the alarm sound for 10 minutes - grid insect protection (to avoid false alarm) - "anti-theft function" (suitable for rental housing - a tool is necessary to take off the detector) <p>Delivered with screws and battery</p> |

| Pack | Cat.Nos | Wireless interconnectable relay actuator |
|------|----------|--|
| 1 | 0 405 14 | <p>Change state upon detection of one of the interconnected devices Cat.No 0 405 28</p> <p>Breaking capacity: 1 A - 30 V</p> <p>Power supply 12 V</p> <p>External back up power supply (not included)</p> <p>Can be interconnected with 10 devices:</p> <ul style="list-style-type: none"> - Cat.No 0 405 28 (smoke alarm detector) <p>Suitable to improve the housing safety</p> <p>Can be linked to Self-contained beacon Cat.No 0 405 10 to indicate the alarm condition to a deaf person, can send the alarm information on a telephone transmitter, can switch on the light to exit easier, can be linked to the home automation</p> |
| 1 | 0 405 10 | <p>Self-contained sounder beacon</p> <p>IP 65 - IK 07</p> <p>Technology LED: white color</p> <p>Power supply: 230 V~ - battery rescued 72H</p> <p>Sound < 60 dB</p> <p>Disabling possible</p> <p>Flash: Dimmable flash from 2 to 150 cd</p> <p>Frequency 1 Hz</p> <p>Suitable for deaf person</p> <p>Supplied with batteries</p> |