

Arteor™

lighting control and visual indication



Support frames and surround plates selection charts **p. 30, 32-35**

Mechanisms supplied with rocker plates, to be equipped with support frames (p. 30) and surround plates (p. 32 to 35)

Pack	Cat. Nos.	Time delay switches	Pack	Cat. Nos.	Illuminated lighting unit
1 1 1 1	5720 55 5740 84 5741 38 5741 37	<p>Interference suppression conforming to standard EN 55022 For timer control of a circuit with the following loads: - 1 000 W incandescent and halogen 230 V~ - 2 300 W resistive (heating) - 400 VA fluorescent and ELV halogen Adjustable from 25 s to 15 min It is possible to install a number of timer switches in parallel on the same circuit With integrated LED 2 wire installation in box min. depth 40 mm 2 modules</p> <ul style="list-style-type: none"> <input type="radio"/> White <input type="radio"/> Magnesium <input type="radio"/> Champagne <input type="radio"/> Soft Alu 	10	5724 52	<p>230 V - 1 W Supplied with 4 coloured labels 1 module</p> <ul style="list-style-type: none"> <input type="radio"/> White
10 10	5724 53 5722 23	<p>Single pole latching relays 10 A - 250 V~ Used to bring functions with low breaking capacity close to the application Resistive : 3 000 W Incandescent : 1 800 W LV halogen : 1 800 W Fluorescent : 400 VA Motors (roller blind type) : 530 W 2 modules</p> <ul style="list-style-type: none"> <input type="radio"/> White <input type="radio"/> Magnesium <input type="radio"/> Champagne <input type="radio"/> Soft Alu 	10 10 10 10	5724 56 5724 55 5724 57 5724 54	<p>Overdoor lighting units Supplied with diffusers and LED 2 modules</p> <ul style="list-style-type: none"> <input type="radio"/> White with red diffuser <input type="radio"/> White with white diffuser
1 1 1 1	5722 27 5727 27 5729 47 5729 46	<p>Skirting lights For installation close to obstacles 2 modules</p> <p>Standard With LED 230 V - 0.2 or 1 W</p> <ul style="list-style-type: none"> <input type="radio"/> White <input type="radio"/> Magnesium <input type="radio"/> Champagne <input type="radio"/> Soft Alu 	10	5724 57	<p>Lamps For locator switch LED 230 V - blue</p>
1 1 1 1	5722 21 5740 82 5740 83 5740 80	<p>With motion detector 100-240 V With IR detection cell and LED When a person passes, the mechanism detects the presence and lights the obstacle The function is equipped with an audible signal that can be disengaged</p> <ul style="list-style-type: none"> <input type="radio"/> White <input type="radio"/> Magnesium <input type="radio"/> Champagne <input type="radio"/> Soft Alu 	10 10 10 10	5724 55 5724 57 5724 54	<p>For indicator switch LED 230 V - red LED 24 V - red LED 12 V - red</p>
1 1 1 1	5722 26 5727 26 5729 45 5729 44	<p>Reading lights Fitted with maintenance-free LEDs LED colours : 3 000 K (neutral white) 230 V power supply - energy class A Screw terminals For installation in the bedhead Offers directional lighting Equipped with a flexible cable so the head can swivel Built-in dimmer Consumption 3-3 W Luminous flux 110 lumen (equivalent to 15 W incandescent) Service life 40 000 hours For installation in back box depth 40 mm min. 2 modules</p> <p>Square version</p> <ul style="list-style-type: none"> <input type="radio"/> White <input type="radio"/> Magnesium 	1 1	5722 57 5727 57	<p>Square version <input type="radio"/> White <input type="radio"/> Magnesium</p>