

# KEOR T EVO 10 kVA

3 102 70 - 3 102 71 - 3 102 72



|   |          |
|---|----------|
| <b>1. GENERAL SPECIFICATIONS .....</b>  | <b>1</b> |
| 1. ARCHITECTURE .....                   | 1        |
| 2. REDUNDANCY .....                     | 1        |
| 3. BYPASS .....                         | 1        |
| 4. CONTROL AND MONITORING .....         | 1        |
| <b>2. TECHNICAL SPECIFICATIONS.....</b> | <b>3</b> |
| 1. GENERAL SPECIFICATIONS .....         | 3        |
| 2. INPUT .....                          | 3        |
| 3. BYPASS .....                         | 3        |
| 4. OUTPUT WITH MAINS (AC-AC) .....      | 3        |
| 5. OUTPUT ON BATTERY (DC-AC) .....      | 3        |
| 6. BATTERY .....                        | 3        |
| 7. ENVIRONMENTAL SPECS .....            | 3        |
| 8. MECHANICAL AND MISCELLANEOUS.....    | 3        |

## 1. GENERAL SPECIFICATIONS

Legrand UPS model KEOR T EVO 10 is an uninterruptible power source with 3-Level IGBT switching technology, high frequency PWM technology, Double Conversion On-line, passing through neutral, with the possibility to have N+X on site parallel redundancy up to total 4 units. Rated Power 10 kVA–10 kW (output PF=1).

Batteries are lead acid, sealed, free maintenance, valve regulated, and arranged inside the UPS in dedicated Drawers. The architecture of this UPS is a Tower type. The cabinet has a compact corresponding to a foot print of 0.21m<sup>2</sup> with possibility to install from 24 up to 36 internal battery blocks. The UPS is also equipped with moving wheels for easier installation and positioning, and floor fixing kit to increase the stability of the cabinet.

### 1. Architecture

Legrand UPS model KEOR T EVO 10 has stand-alone architecture. UPS is composed by following parts:

- IGBT Rectifier/PFC
- 3-Level IGBT Switching Technology
- Digital Signal Processor (DSP)
- 3.5" TFT Touch Panel
- Automatic Bypass
- Dual Input Bypass
- Internal Manual Bypass
- Standard Internal Backfeed Protection
- Internal Battery Drawer Shelves

The UPS can be easily configured on site, by the authorized personnel, to operate in parallel. Also it is possible to arrange the dedicated bypass input by removing bridge connection on each input phase. Legrand KEOR T EVO 10 has 3-Level IGBT

switching technology and there is no transformer in the unit. These provide high efficiency for the unit.

Backfeed protection provides additional protection at the input in the event of static bypass is short circuited.

By using internal backfeed contactor in bypass line provides safety when fault situation occurs in static bypass line and prevents upstream energy to the input. The internal backfeed protection provides an easy on site installation without any additive cabling or special MCCB type in the upstream distribution panel.

### 2. Redundancy

The Redundancy of the UPS allows N+X redundant configurations. Up to 4 units of same size UPS can be connected in parallel.

### 3. Bypass

KEOR T EVO has internal both static bypass and mechanical (maintenance) bypass as standard. Addition to this input and bypass inputs can easily be separated to obtain dual input by removing the bridge on the connector.

### 4. Control and monitoring

KEOR T EVO is equipped with a touch screen graphic TFT display that provides mimic UPS diagram with relevant information, measurements, statuses and alarms of the UPS in different languages. Below this display, there is a multicolor LED bar showing status of UPS.

- GREEN: Normal or ECO Mode Operation
- ORANGE: Bypass or Battery Operation
- RED: Load not Supplied

## KEOR T EVO 10 kVA

3 102 70 - 3 102 71 - 3 102 72

A dedicated software of remote monitoring and management, installed on a PC connected to the UPS, allows to check and set all working parameters of KEOR T EVO (the same functions available on the UPS control panel) and, furthermore, to schedule and program computer remote shutdown.

Optional software (UPSMAN) or Net Interface card (CS141 SK) allow the multi server shutdown and UPS remote control on the LAN.

Also, standard interface board comes with:

- RS232 Serial Communication Port
- Emergency Power Off (UPS OFF)
- Generator Contact (GEN ON)
- 4pcs programmable Dry Contact Information
- 2 contactor relays for Bypass and Battery
- ModBus (over RS485, with 2400 Baud Rate)

Standard Dry Contact Alarms are General Alarm, Bypass Active, Input Failure and Synchronization OK.

Addition to these: High Temperature, Battery Test Failure, Output Failure alarms can be assigned to the contacts. Each alarm can be assigned to separate contacts but also one alarm may be assigned to all contacts. KEOR T EVO front panel is controlled by DSP microprocessor which works together with DSP microprocessors in rectifier and inverter; by display is possible to check all measurements, working parameters and status of the system.

Here follow the measurements and working parameters available on the display:

### RECTIFIER (Input)

Voltage (Vac), per phase  
Current (Aac), per phase  
DC BUS Voltage ( $\pm$  Vdc)

### FREQUENCY

Input Frequency (Hz)  
Output Frequency (Hz)

### BATTERY

Voltage ( $\pm$ Vdc)  
Current ( $\pm$ Adc)  
Temperature  
Autonomy (minute)

### INVERTER (Output)

Voltage (Vac), per phase  
Current (Aac), per phase  
Apparent Power (kVA), per phase  
Active Power (kW), per phase  
Power Factor (load), per phase  
Bypass Voltage, per phase  
Load (%), per phase

The UPS allows also the following settings by display

### OUTPUT

Voltage (380/400/415)  
Frequency (50Hz/60Hz)

### BATTERY

Battery String  
Battery Capacity

### COMMAND MENU

Priority (Online (Inverter) /Green (Bypass))  
Battery Test (KEOR T EVO tests the battery automatically once each 90 days)

Maintenance (Rectifier, Inverter, Bypass, Load Supply – YES/NO)

### RELAY FUNCTIONS

Relay 1 (General Alarm as standard)  
Relay 2 (Input Failure as standard)

Each relay can be adjusted from 7 different alarms

### PARALLEL MODE

Parallel Mode  
(Enable/Disable(Single))  
UPS ID  
Redundancy (+1, +2, +3)  
Operation Mode (Redundancy  
Power Increase)

### OPTIONS

Alarm Voice (Enable/Disable)  
Key Voice (Enable/Disable)  
Warning Window (Enable/Disable)

### OTHER

Display Brightness (0 to 100)  
Emergency Power Off (NC/NO)  
Generator Mode (NC/NO)  
ModBus ID  
Time (hh:mm. Required for Event Log stamp)  
Date (dd:mm:yyyy. Required for Event Log stamp)  
Language (English, Italian, French, German, Spanish, Portuguese, Turkish, Russian, Dutch, Polish)

Legrand KEOR T EVO displays up to 500 last events. Events are stored in EEPROM using FIFO method. Order number of last occurred event is 001 and the last event in the list is erased when there are 500 events. The UPS KEOR T EVO has the CE Mark accordingly with the EU Directives 2014/35/EU, 2014/30/EU of 26 February 2014 and it complies with following standards:

- EN 62040-1 "General rules for electric safety"
- EN 62040-2 "Electromagnetic compatibility and immunity (EMC)"
- EN 62040-3 "Performances and testing rules"

# KEOR T EVO 10 kVA

3 102 70 - 3 102 71 - 3 102 72

## 2. TECHNICAL SPECIFICATIONS

### 1. General specifications

|                                       |  |
|---------------------------------------|--|
| UPS Topology                          | On line double conversion<br>VFI SS 111              |
| Architecture of the UPS               | Stand alone, transformerless,<br>On-Site Paralleling |
| In/Out phase Configuration            | Three phase-Three phase                              |
| Neutral                               | Neutral Passing through                              |
| Switching Technology                  | 3-Level IGBT   |
| Backfeed Protection                   | Internal, standard                                   |
| Output wave form on mains operation   | Sinusoidal   |
| Output wave form on battery operation | Sinusoidal   |
| Standards                             | EN 62040-1, EN 62040-2,<br>EN 62040-3                |

### 2. Input

|                 |   |
|-----------------|---|
| Nominal Voltage | 400 3ph+N+PE  |
| Voltage Range   | 358 - 459 Ph-Ph full load<br>208 - 459 Ph-Ph half load" |
| Frequency       | 45 - 65Hz   |
| THDin           | < 5% at full load                                       |
| Power Factor    | > 0.99  |

### 3. Bypass

|                 |  |
|-----------------|--|
| Nominal Voltage | 400 3ph+N+PE                           |
| Voltage Range   | 380/400/415V -18% +15%<br>(adjustable) |
| Frequency       | 47-53Hz or 57-63Hz (adjustable)        |
| Bypass Type     | Static and Electro-mechanic            |
| Transfer Time   | Zero                                   |
| Manual Bypass   | Built-in                               |

### 4. Output with mains (AC-AC)

|   |  |
|---|--|
| Nominal Voltage                         | 380, 400, 415 3ph+N+PE                   |
| Nominal Power                           | 10.000 VA                                |
| Active Power                            | 10.000 W                                 |
| Voltage variation (static)              | ± 1%                                     |
| THDv on nominal power (linear load)     | < 2%                                     |
| THDv on nominal power (non-linear load) | < 4%                                     |
| Frequency                               | 50 Hz or 60 Hz (selectable)              |
| Frequency tolerance                     | ± 0,1% Synchronized with input frequency |
| Current Crest Factor                    | 2.5:1 accordingly to IEC 62040-3         |
| Overload capability:                    |  |
| 10 min                                  | 125% load with no bypass                 |
| 60 sec                                  | 150% load with no bypass                 |

### 5. Output on battery (DC-AC)

|   |                                  |
|---|----------------------------------|
| Nominal Voltage                         | 380, 400, 415 3ph+N+PE           |
| Nominal Power                           | 10.000 VA                        |
| Active Power                            | 10.000 W                         |
| Voltage variation (static)              | ± 1%                             |
| THDv on nominal power (linear load)     | < 2%                             |
| THDv on nominal power (non-linear load) | < 4%                             |
| Frequency                               | 50 Hz or 60 Hz (selectable)      |
| Frequency tolerance                     | ± 0,01% free run                 |
| Current Crest Factor                    | 2.5:1 accordingly to IEC 62040-3 |
| Overload capability:                    |                                  |
| 10 min                                  | 125%                             |
| 60 sec                                  | 150%                             |

### 6. Battery

|   |  |
|---|--|
| Type                                    | Lead Acid, sealed, free maintenance VRLA               |
| Unit Capacity                           | 7 or 9 Ah (12V)  |
| Nominal UPS Battery Voltage             | ±144 Vdc (max ±192 Vdc)                                |
| Nominal n. of possible internal battery | 24pcs (12x2)   |
| Max. n. of possible internal battery    | 32pcs (16x2)   |
| Battery charger type                    | IGBT Rectifier also charges batteries                  |
| Charging Cycle                          | Intelligent with boost charge and advanced management" |
| Max Charging Current without derating   | 2 A  |

### 7. Environmental specs

|                             |                       |
|-----------------------------|-----------------------|
| Noise level @ 1m (50% load) | < 51dBA               |
| Operating temperature range | from 0°C to +40°C     |
| Stock temperature range     | from -20°C to +50°C   |
| Humidity range              | 20-95% not condensing |
| Protection degree           | IP20                  |

### 8. Mechanical and miscellaneous

|   |   |
|---|---|
| Net Weight without batteries <sup>1</sup> | 78 kg   |
| Dimensions (HxW xD)                       | 102 0x 265 x 800 mm   |
| Colour                                    | Enclosure: RAL 7016Front Door<br>Metal: RAL 9005  |
| Communication Interface                   | 1 serial port RS232,<br>1 RS485, 1 smart port for internal SNMP,<br>4 Dry Contacts, 1 EPO, 1 GENSET |
| Input/Output connections                  | 3Ph + N + PE  |

<sup>1</sup> The weigh depends by the number of the installed batteries accordingly with the required autonomy.