

## Electronic time-lag switches



Designed for supply busbar compatibility  
Power supply: 230 V~ - 50/60 Hz  
Switches a lighting circuit for a specific time  
Self-protection in the event of blocked pushbutton


Pack	Cat.Nos	Time-lag switch	Number of modules
10	4 126 02	<b>Resettable</b> 230 V~ - 50/60 Hz Timing adjustable from 0.5 sec to 10 min Manual override contact Output 16 A - 250 V~ - $\mu \cos \varphi = 1$ 2000 W incandescent/halogen 2000 W halogen - 230 V~ 1000 VA fluo - series compensated 120 VA fluo - parallel compensated 14 $\mu F$ 100 VA compact fluorescent 1000 W energy saving lamp automatic 3-wire or 4-wire connection	1
10	0 047 04	<b>Multi-function time-lag switch</b> Resettable 230 V~ - 50/60 Hz Timing adjustable from 0.5 sec to 12 min Operation with 3 or 4 wires a utomatically recognised by the time-lag switch - Inputs for separate control 8-230 V (presence detection, lighting control by door entry system etc.) - Switch-off pre-warning function, - Long duration function (1 hour) and manual switch-off Output 16 A - 250 V~ - $\mu \cos \varphi = 1$ 3680 W incandescent/halogen 2000 W halogen 230 V~ 1000 VA fluo - parallel compensated $\leq 100 \mu F$ 2000 VA compact fluorescent 500 W halogen lamp + ferromagnetic transformer 2000 W halogen lamp + electronic transformer - Specially suited to energy saving lamps 1000 W	1
1	0 497 83	<b>Automatic staircase time-lag switch for wall mounting 230 V - 50 Hz</b> Switches a lighting circuit during a determined period Controlled by illuminated push-button 50 mA max 3 wire connection Output : 1 contact Contact rating 10 A - 250 V~ - $\cos \varphi = 1$ Type of delay adjustable Electronic 0.5 to 10 min.	Resettable

## Electronic time-lag switches


### wiring diagrams

#### Multi-function time-lag switch


##### 4-wire




##### 3-wire



#### Multi-function time-lag switch: lighting control by door entry system



#### Switch-off pre-warning function



For fluorescent and energy saving lamps the switch-off period is longer than 0.3 s, because of re-starting time required by the lamps