

PRODUCT TECHNICAL DATA SHEET

| Myrius nextgen™ | Ref . No. :679362/ 679377 | |
|-----------------|---------------------------|-------|
| Wireless switch | Date : 06-10-2021 | Rev.1 |



Note :This product is a connected accessory which requires you to install the "Legrand connected (IOT) range" connected starter pack first.

1. USE

Wireless control for ON/OFF light function or connected socket outlet.

Controls micromodule products, connected socket outlets and connected dimmer switches. Can be used as a two-way switch or to control a lighting group.

2.Type

IoT Wireless switch

No. of modules : Monoblock Colour: White / Charcoal Grey

Mounting: Fixes directly on the wall or screws onto a flush-mounting box.

• Fits on a piece of furniture (movable).

Can be combined with 20 connected light switches with dimming option, connected socket outlets or micromodules.


3.OVERALL DIMENSIONS

Length: 86 mm Width: 86 mm Height: 12 mm Weight (g): 218

4.CONNECTION

Through wireless network


5.OPERATION



OFF when pressed at the top and dimming when held down until released

 useful during installation when pressed, burst flashes red if the battery power is lo

ON when pressed the bottomand dimming when held down until released



RESET button used to return to factory settings

Refer product instruction sheet

6.TECHNICAL CHARACTERISTICS

6.1 Material Characteristics

Rocker: Acrylonitrile Butadiene Styrene (ABS)

Mechanism casing : Polycarbonate

Mechanism : Electronic Self-extinguishing: 650° C / 30 s.

6.2 Electricals Characteristics

Powered by a CR2032 - 3 V lithium battery (supplied) Battery life: 8 years for 10 activations a day (tentative) ZigBee radio technology frequency: 2.4 GHz to 2.4835 GHz

Wireless mesh network, self-adaptive and secure (AES 128), conforming to standard IEEE 802.15.4 (LR-

WPAN)

Power level: < 100 mW 6.3 Climate characteristics Storage temperature: 0° C to + 45° C

Usage temperature: +5° C to + 45° C

7.CARE

Clean the surface with a cloth.

Do not use acetone, tar-removing cleaning agents or trichloroethylene.

Caution: Always test before using special cleaning products. Take care to recycle the battery appropriately.

8.CONFORMITY - APPROVALS

Equipment Type Approval (ETA) through self-declaration issued under O.M. No. ETA-WPC /Policy/2018-19 dated 26 February, 2019