

# Shaver Socket




Device for the supply of electric shavers requiring either a 240V or 115V supply and having a power consumption not exceeding 20VA. Accepts the following types of plug: BS, Euro, US, Australian and Chinese. (Supplied with M3.5 screws for Flush mounting or surface mounting BS boxes.)

## 2. RANGE

#### **Shaver Socket**

7 482 41	Satin Brass
7 484 41	Brushed stainless steel
7 486 41	Polished stainless steel

# 3. DIMENSIONS (mm)



References	A	В	С	D
7 482 41 7 484 41 7 486 41	86	146	50.8	40.6

# 4. CONNECTION

Types of terminals: auto terminal Terminal capacity: 2 X 1.5 mm<sup>2</sup> 2 X 2.5 mm<sup>2</sup> Recommended stripping length: 13 mm

# **5. TECHNICAL CHARACTERISTICS**

#### 5.1 Material characteristics

Plate: PC Frame: PC

Base: PC

Self-extinguishing:

- + 850° C / 30 s for insulating parts holding live parts in place
- + 650° C / 30 s for other parts made of insulating materials

#### 5.2 Electrical characteristics

Transformer: primary and secondary 240 V - 115/240 V Frequency: 50/60 Hz Power: 20VA Max.

## 5.3 Climatic characteristics

Storage temperatures:  $-10^{\circ}$ C to  $+70^{\circ}$ C Operating temperatures:  $-5^{\circ}$ C to  $+35^{\circ}$ C

#### 5.4 Mechanical characteristics

Impact test: IK04 Protection against solids & liquids: IP24

## 6. CLEANING

Surface cleaning with a soft, slightly damp cloth. Do not use: acetone, tar remover, trichloroethylene

## 7. CONFORMITY - APPROVALS

Conform to BS EN 61558-2-5.