


Arteor™ with Netatmo - British Standard Connected starter pack





General control

1. USE

This pack enables you to create a connected installation in your home.

It can be used to control lighting, roller shutters and electrical equipment plugged into connected products

- using your smartphone and the Home + Control app
- using voice assistants
- from the general control at the entrance to your home

Comprises:

• A gateway (Zigbee relay/WiFi)

Installation in 1-gang box 35 mm deep (minimum).


Claw and/or screw fixing.


- A wireless general control, used to control leaving home/coming home scenes involving lights, roller shutters and connected sockets.
- Fixes directly on the wall or screws onto a flush-mounting box.
- Fits on a piece of furniture (movable).

2. RANGE


Description	White	Magnesium	Soft Alu	Champagne
Gateway: To be equipped with support frame and plate				
Additional wireless general control: Supplied with secable support frame, rocker plate and a battery. Equipped with an LED indicator (configuration) and a RESET button (hidden) used to return to factory settings. Repositionable self-adhesive fixings (supplied).	5 746 01	5 746 02	5 746 03	5 746 04

3. DIMENSIONS (mm)





Gateway	Α	В	С	D
	45	45	46	12.5







Cat. Nos: 5 746 01/02/03/04

Wireless General Control	Α	В	B'	C
	82	116.5	82	12

Arteor™ with Netatmo - British Standard Connected starter pack

4. OPERATION






Arrival scenario when pressed at the top: By default, switches on the connected sockets Can be customised with the Home + Control app

- LED indicator:
- useful during installation
- when pressed, burst flashes red if the battery power is low

Leaving scenario when pressed at the bottom: By default, switches off all the lights and close shutters/curtains in the installation. Can be customised with the Home + Control app.



RESET button used to return to factory settings



The starter pack is pre-paired at the factory.

Never perform a factory RESET on the gateway module and the wireless general control at the same time, as this may render them unusable.

5. CONNECTION

Gateway

Terminal type: with screws Terminal capacity: 2 x 2.5 mm² Stripping length: 9 mm

6. TECHNICAL CHARACTERISTICS

■ 6.1 Mechanical characteristics

Gateway:

Protection against impacts: IK 04

Protection against solid bodies and/or liquids: IP 40 monted product

General control:

Protection against impacts: IK 02

Protection against solid bodies/liquids: IP 20

■ 6.2 Material characteristics of gateway

Cover plate: PC Mechanism casing: PC Halogen-free

UV-resistant

Self-extinguishing:

850°C/30 s for insulating components holding live parts in place. 650°C/30 s for other insulating components.

6. TECHNICAL CHARACTERISTICS (continued)

Cat. Nos: 5 746 01/02/03/04

■ 6.3 Material characteristics of general control

Mechanism casing with grid: Fibreglass-reinforced (20%) PC Halogen-free

UV resistant

Self-extinguishing: 650°C/30 s

■ 6.4 Electrical characteristics

Voltage: 110/230 V~

Standby consumption: 10 mA

WiFi technology

Frequency: 2.4 GHz to 2.4835 GHz

Power level: < 100 mW

Range: 200 m of unobstructed space

10 m recommended between products indoors

General control

Powered by a CR2032 - 3 V lithium battery (supplied) Battery life: 8 years for 10 activations a day

■ 6.5 Climate characteristics

Storage temperature: 0°C to + 45°C Usage temperature: +5°C to + 35°C

7. CARE

Clean the surface with a cloth.

Do not use acetone, tar-removing cleaning agents or trichloroethylene.

Resistant to the following products:

Hexane, methylated spirit, soapy water, diluted ammonia, bleach diluted to 10%, window-cleaning products, pre-impregnated wipes.

Caution: Always test before using special cleaning products.



Take care to recycle the battery appropriately.

8. STANDARDS AND APPROVALS

The undersigned, LEGRAND, declares that the radio-electric equipment type (5 746 01/02/03/04) complies with directive 2014/53/EU. The full text of the EU declaration of conformity is available on the following website: www.legrandoc.com