



Cát. No(s): CB0442

2-speed exhaust fan kit



Micromodule for 2-speed exhaust fan



Wireless control for exhaust fan

1. USE

Pack to control 2-speed exhaust fan angine.

The complete exhaust fan Kit includes:

- a micromodule for 2-speed exhaust fan,
- a wireless control for 2-speed exhaust fan.

Can also be added to a connected installation "... with Netatmo" equipped with a Control socket or a Control module.

Possibility to add additionnal wireless exhaust fan Cat. Nos CB0411/CN0411/CT0411).

2. RANGE

Description exhaust fan control kit Cat. No CB0442



Micromodule for 2-speed exhaust fan

With LED indicator (configuration) and RESET button (hidden) used to return to factory settings.





Connected wireless control for 2-speed exhaust fan. Supplied complete with battery.

With LED indicator (configuration) and RESET button (hidden) used to return to factory settings.

Repositionable self-adhesive fixings supplied.


3. DIMENSIONS (mm)





Kit exhaust fan CN0442	Α	В	С	D
Micromodule	45	22.5	45	9

3. DIMENSIONS (mm) (continued)





Kit exhaust fan CB0442	Α	В	С	D
Wireless control	82	90	13	-

4. CONNECTION

Micromodule


Number of terminals: 4 Terminal type: with screws

Terminals capacity: $1 \times 2.5 \text{ mm}^2 - 2 \times 1.5 \text{ mm}^2$

Stripping length: 7 mm


5. FUNCTION


Micromodule



2-speed exhaust fan kit

5. FUNCTION (continued)





RESET button used to return to factory mode.

6. TECHNICAL CHARACTERISTICS

■ 6.1 Mechanical chacaracteristics

Micromodule:

Protection against impacts: IK 04

Protection against solid/bodies and liquids: IP 20

Wireless control:

Protection against impacts: IK 02

Protection against solid/bodies and liquids: IP 40

■ 6.2 Material characteristics

Micromodule:

Casing: PC

Wireless control:

Mechanism casing with grid: Fibreglass-reinforced (10%) PC

Plate: ABS + PC White RAL 9003 Rocker: White ABS RAL 9003

Halogen-free

UV-resistant

Self-extinguising:

 $850^{\circ}\text{C}/30~\text{s}$ for insulating parts holding live parts in place.

650°C/30 s for the other insulating components.

■ 6.3 Electrical characteristics

Frequency band: 2.4 to 2.44835 GHz

Power level: < 100 mW

Micromodule:

Voltage: 100/240 V~ Frequency: 50/60 Hz

Standby consumption: 3.2 mA

	Motor
240 Vac max.	1 x 500 VA
100 Vac max.	1 x 270 VA

Wireless control:

Powered by a CR2032 - 3 V lithium battery (supplied) Battery life: 8 years for 10 activations a day

■ 6.4 Climate characteristics

Storage temperature: 0°C to $+45^{\circ}\text{C}$ Usage temperature: $+5^{\circ}\text{C}$ to $+55^{\circ}\text{C}$

7. CARE

Clean the surface with a cloth.

Do not use acetone, tar-removing cleaning agents or trichloroethylene.

Resistant to the following products: Hexane (EN 60669-1), methylated spirit, soapy water, diluted ammonia, bleach diluted to 10%, window-cleaning products, pre-impregnated wipes.

Caution: Always test before using special cleaning products.

The plates must not be painted.



Take care to recycle the battery appropriately

8. ACCESSORIES

0 648 71: Repositionable adhesives for wireless control (supplied)

9. STANDARDS AND APPROVALS

The undersigned, LEGRAND, declares that the radio-electric equipment type (CB0442) complies with directive 2014/53/EU.

The full text of the EU declaration of conformity is available on the following website: **www.legrand.com/ecatalogue**

Compliant with installation and manufacturing standards. See e.catalogue.